



ARA58-F-EN



ARA58-F-EN



ARA58-F-AUX

- Simple installation, connects directly to PCB's connector through the serial line.
- Supports GSM/WCDMA/LTE-FDD/LTE-TDD.
- Sends messages to alert you of events. ARA58-F-EN also supports remotely controlling the device through the message.
- Calls to inform you of alarms. ARA58-F-EN also supports leaving a voice message.
- Used with wired control panel ARC2008C/ARC2016C/ARC9016C/ARC3008C.

Technical Specification

Port

Network Mode

ARA58-F-EN: GSM: 900/1800MHz, WCDMA: B1/B5/B8, LTE-FDD: B1/B3/B5/B7/B8/B20, LTE-TDD: B38/B40/B41
 ARA58-F-AUX: GSM: 850/900/1800/1900 MHz, WCDMA: B1/B2/B5/B8, LTE-FDD: B1/B2/B3/B4/B5/B7/B8/B28, LTE-TDD: B40

General

Power Consumption	4 W
Operating Temperature	-10 °C to +55 °C (+14 °F to +131 °F)
Operating Humidity	10%–90% (RH)
Storage Temperature	-40 °C to +80 °C (-40 °F to +176 °F)
Packaging Dimensions	238 mm × 109 mm × 45 mm (9.37" × 4.29" × 1.77")
Net Weight	< 90 g (0.20 lb)

Dimensions (mm/inch)

